



# EISA Lamp Cross Reference...

WideLite®



400W Metal Halide (non-compliant)	
Input Watts	458
Mean Lumens	23,500
Mean LPW	51
Lamp Life	20,000

320W Pulse Start (EISA compliant - SAVE ENERGY)	
Input Watts	368
Mean Lumens	26,000
Mean LPW	71
Lamp Life	20,000

350W Pulse Start (EISA compliant - SAVE ENERGY)	
Input Watts	400
Mean Lumens	29,000
Mean LPW	73
Lamp Life	20,000

400W Pulse Start (EISA compliant - LESS FIXTURES)	
Input Watts	452
Mean Lumens	35,000
Mean LPW	77
Lamp Life	20,000

450W Pulse Start (EISA compliant - LESS FIXTURES)	
Input Watts	505
Mean Lumens	40,000
Mean LPW	79
Lamp Life	20,000

250W Metal Halide (non-compliant)	
Input Watts	295
Mean Lumens	17,000
Mean LPW	58
Lamp Life	10,000

175W Metal Halide (non-compliant)	
Input Watts	210
Mean Lumens	9,100
Mean LPW	43
Lamp Life	10,000

200W Pulse Start (EISA compliant - SAVE ENERGY)	
Input Watts	240
Mean Lumens	16,800
Mean LPW	70
Lamp Life	12,000

250W Pulse Start (EISA compliant - LESS FIXTURES)	
Input Watts	291
Mean Lumens	20,000
Mean LPW	69
Lamp Life	15,000

150W Pulse Start (EISA compliant - SAVE ENERGY)	
Input Watts	185
Mean Lumens	10,500
Mean LPW	57
Lamp Life	15,000

175W Pulse Start (EISA compliant - LESS FIXTURES)	
Input Watts	208
Mean Lumens	14,000
Mean LPW	67
Lamp Life	15,000

150W Metal Halide (non-compliant)	
Input Watts	185
Mean Lumens	10,000
Mean LPW	54
Lamp Life	15,000

100W Pulse Start (EISA compliant - SAVE ENERGY)	
Input Watts	129
Mean Lumens	5,900
Mean LPW	46
Lamp Life	15,000

150W Pulse Start (EISA compliant - LESS FIXTURES)	
Input Watts	185
Mean Lumens	10,500
Mean LPW	57
Lamp Life	15,000

NOTES:

- 1) All information provided is to be used as a guide only and is subject to change without notice.
- 2) Data may vary per lamp manufacturer, orientation, clear vs. coated, etc.
- 3) Additional lamp choices may be available (refer to specific lamp catalogs for full details).
- 4) Contact Wide-Lite for any assistance as needed to properly cross existing and new specifications.

PT#: WLCS0111A1008